



SHENZHEN FINA INDUSTRIAL CO. , LTD.

Address: D Building, Changyuan Industrial Zone, Xili, Nanshan District, Shenzhen, China

TEL/FAX: 0086-755-26700956 Mobile: 0086-13556849700

E-mail: sales@finasecurity.com

Website: www.finasecurity.com

Touch Keyboard GSM PSTN Dual Network LCD Alarm System



FI6021	FI6022(Newest)	FI6023
<p>Press keyboard Icons Menu</p>	<p>Full Touch Panel</p>	<p>While/Black house optional</p>

New Value-added Features

- **Touch Keyboard with intelligent LCD display-Easy to program & operate**
- **Multi Language available:** English\ German\ French\ Russian\ Dutch\ Danish,Italian etc to meet different market demand
- **868Mhz Rechargeable PIR motion sensor/Door sensor available to save battery cost**

Main features

1. Touch keypad; LCD displays Date, Day of the week, Time, and current Armed Status
2. Supported Languages: Simplified Chinese\ Traditional Chinese\ English\ German\ French\ and more to meet different market needs..
3. GSM 2/4 Band optional,900/1800Mhz or 850/900/1800/1900Mhz
4. Auto calling alert & SMS Alert while alarm is triggered
5. 30 wireless zones (Each zone supports up to 4 sensors) and 2 dedicated zones for remotes (Supports up to 4 remotes or wireless keypads per zone). Support 8 more wired zones(Optional).
6. Can preset up to 5 phone numbers and dial in sequence.
7. Intelligent logic analysis technology, corresponding zone number and sensor name can be displayed.
8. Record up to a 10 second greeting for the auto-dialer, Then play the greeting back.
9. Arm\ Disarm the system by 5 ways: SMS, Main Host (Keypad), Wireless Keypad, Keychain Remotes, or even remotely by phones. (PSTN alarm don't support SMS)
10. Available in AC\DC with Low-voltage Indicators
11. Learning sensors to alarm host, very easy operation.
12. Non-volatile chip, information stored automatically when off power.
13. Check door/window status automatically (This is when the system is disarmed only, if a door is opened, it will sound fast "bi bi bi")
14. Support wireless "ding-dong" doorbell function (Optional)
15. Support CID uploading to CMS (Center monitoring Station), can user our GSM CID connector to have this function.
16. Disconnection alarm, auto priority to occupy the telephone and monitoring function to hear what is happening.
17. Built-in Li-Ion backup battery, it will alert when low power or without external power supply.
18. Store up to 100 alarm records and 100 arm\disarm records











Standard Packing kits

					
1 x GSM Alarm Unit	1 x Wireless PIR sensor	1 x Wireless door sensor	2 x remote controllers	1 x Wireless Strobe Siren	Power Adapter

Specification

- Working power: AC=100~230V, DC=12V 1A
- Built-in Li-Ion backup battery: 3.7V 1200mAH(rechargeable)
- Standby: around 16 hours, Full charging time: 12 hours
- 2-Band GSM: GSM900/1800Mhz (4-Band is optional: 850/900/1800/1900Mhz)
- GSM transmit power: 2W
- Receiving and emitting frequency: 433MHz
- Working condition:
Temperature: -10°C ~ 50°C Humidity: <80%
- Product dimension:150×107×26(mm)
- Static current:<50mA (when not charging) Alarm current:<500mA

Other Sensors & Detectors

				
Wireless/Wired smoke detector	Rechargeable PIR Sensor	Roller shutter sensor	Rechargeable Door Sensor	IR Fence detector
				
Wireless/wired gas detector	Ceiling PIR Sensor	Panic button	Wireless Keyboard	Wireless strobe siren



GSM PSTN Alarm with LCD Touch Screen



Warranty & Return

If the item you received is defective in any way, contact us within the warranty period and we will replace the same item type to you. The warranty covers against defective workmanship only, misuse or willful damage will render the warranty void.

- Defective products must be returned within 15 days from the date you placed your order. We will refund you the full product price (no shipping and packing fee) Return policy is exchange only, in all cases, buyers pay for shipping at their own cost to return products for exchange or refund, sellers pay for the resending fee.

Replacement will be made upon receipt the returned item.

Thanks for your attention to our company and products!

Welcome to contact us for detailed quotations!

Business Email: Sales@finasecurity.com